

# STANDARD COPPER TUBE TERMINALS | Copper Tube Lugs

## COPPER TUBE TERMINALS



Code	Cable Size mm <sup>2</sup>	Stud Size	(A)	(B)	(W)	(E)	(F)	(D)	(L2)	Palm Thickness
16-6	16	6	5.6	7.5	10.8	8.8	6.2	5.5	30.0	2.0
16-8	16	8	5.6	7.5	13.5	8.0	7.0	5.5	30.0	1.6
16-10	16	10	5.6	7.5	15.0	10.9	9.6	5.5	35.5	1.5
16-12	16	12	5.6	8.0	18.0	12.0	10.0	5.5	42.0	1.3
25-6	25	6	7.0	9.4	13.8	8.8	6.2	7.0	32.5	2.4
25-8	25	8	7.0	9.4	13.8	8.0	7.0	7.0	32.5	2.4
25-10	25	10	7.0	9.4	16.0	10.9	9.6	7.0	38.0	2.1
25-12	25	12	7.0	9.4	18.0	10.5	10.0	7.0	38.0	1.9
35-6	35	6	8.2	10.6	15.3	8.8	6.2	8.2	35.0	2.4
35-8	35	8	8.2	10.6	15.3	8.0	7.0	8.2	35.0	2.4
35-10	35	10	8.2	10.6	15.3	10.9	9.6	8.2	40.5	2.4
35-12	35	12	8.2	10.6	18.0	10.5	10.0	8.2	40.5	2.2
50-6	50	6	9.5	11.9	17.4	8.8	6.2	9.5	37.0	2.5
50-8	50	8	9.5	11.9	17.4	8.0	7.0	9.5	37.0	2.5
50-10	50	10	9.5	11.9	17.4	10.9	9.6	9.5	42.5	2.5
50-12	50	12	9.5	11.9	17.4	10.9	9.6	9.5	42.5	2.5
70-6	70	6	11.5	14.5	20.9	8.8	6.0	11.5	40.5	3.0
70-8	70	8	11.5	14.5	20.9	8.0	7.0	11.5	46.0	3.0
70-8	70	10	11.5	14.5	20.9	10.9	9.6	11.5	46.0	3.0
70-12	70	12	11.5	14.5	20.9	10.5	10.0	11.5	50.0	3.0
70-14	70	14	11.5	14.5	20.9	13.0	13.0	11.5	50.0	3.0
70-16	70	16	11.5	14.5	20.9	13.0	13.0	11.5	50.0	3.0
95-6	95	6	13.5	16.7	24.3	10.9	9.6	19.0	49.5	3.2
95-8	95	8	13.5	16.7	24.3	10.9	9.6	19.0	49.5	3.2
95-10	95	10	13.5	16.7	24.3	10.9	10.0	19.0	49.5	3.2
95-12	95	12	13.5	16.7	24.3	10.5	10.8	19.0	49.5	3.2
95-14	95	14	13.5	16.7	24.3	13.0	13.0	19.0	56.0	3.2
95-16	95	16	13.5	16.7	24.3	13.0	13.0	19.0	56.0	3.2

Call the Remora sales team at **01226 352 000**

Challenge us - We find a solution