

STANDARD COPPER TUBE TERMINALS | Copper Tube Lugs

COPPER TUBE TERMINALS



Code	Cable Size mm ²	Stud Size	(A)	(B)	(W)	(E)	(F)	(D)	(L2)	Palm Thickness
300-10	300	10	23.0	28.0	41.0	18.0	17.0	37.0	97.0	5.0
300-12	300	12	23.0	28.0	41.0	18.0	17.0	37.0	97.0	5.0
300-14	300	14	23.0	28.0	41.0	18.0	17.0	37.0	97.0	5.0
300-16	300	16	23.0	28.0	41.0	18.0	17.0	37.0	97.0	5.0
300-20	300	20	23.0	28.0	41.0	18.0	17.0	37.0	97.0	5.0
400-10	400	10	27.0	32.0	47.3	22.0	22.0	38.0	108.0	5.0
400-12	400	12	27.0	32.0	47.3	22.0	22.0	38.0	108.0	5.0
400-14	400	14	27.0	32.0	47.3	22.0	22.0	38.0	108.0	5.0
400-16	400	16	27.0	32.0	47.3	22.0	22.0	38.0	108.0	5.0
400-20	400	20	27.0	32.0	47.3	22.0	22.0	38.0	108.0	5.0
500-10	500	10	30.0	36.0	53.0	28.0	24.0	38.0	117.0	6.9
500-12	500	12	30.0	36.0	53.0	28.0	24.0	38.0	117.0	6.9
500-14	500	14	30.0	36.0	53.0	28.0	24.0	38.0	117.0	6.9
500-16	500	16	30.0	36.0	53.0	28.0	24.0	38.0	117.0	6.9
500-20	500	20	30.0	36.0	53.0	28.0	24.0	38.0	117.0	6.9
630-10	630	10	33.8	44.0	63.0	25.0	23.0	46.0	127.0	10.2
630-12	630	12	33.8	44.0	63.0	25.0	23.0	46.0	127.0	10.2
630-14	630	14	33.8	44.0	63.0	25.0	23.0	46.0	127.0	10.2
630-16	630	16	33.8	44.0	63.0	25.0	23.0	46.0	127.0	10.2
630-20	630	20	33.8	44.0	63.0	25.0	23.0	46.0	127.0	10.2
800-10	800	10	38.0	49.0	70.0	34.0	34.0	56.0	164.0	11.0
800-12	800	12	38.0	49.0	70.0	34.0	34.0	56.0	164.0	11.0
800-14	800	14	38.0	49.0	70.0	34.0	34.0	56.0	164.0	11.0
800-16	800	16	38.0	49.0	70.0	34.0	34.0	56.0	164.0	11.0
800-20	800	20	38.0	49.0	70.0	34.0	34.0	56.0	164.0	11.0
1000-10	1000	10	42.5	53.0	77.0	34.0	34.0	56.0	169.0	10.5
1000-12	1000	12	42.5	53.0	77.0	34.0	34.0	56.0	169.0	10.5
1000-14	1000	14	42.5	53.0	77.0	34.0	34.0	56.0	169.0	10.5
1000-16	1000	16	42.5	53.0	77.0	34.0	34.0	56.0	169.0	10.5
1000-20	1000	20	42.5	53.0	77.0	34.0	34.0	56.0	169.0	10.5

Call the Remora sales team at **01226 352 000**

Challenge us - We find a solution